

Serial No. 09/502,882

**IN THE CLAIMS**

1 1. (Currently amended) A data transmission system comprising:  
2 a first plurality of Gigabit Ethernet input/output ports, each port being adapted to  
3 be coupled to a first Gigabit Ethernet link carrying data packets;  
4 a multiplexer interface coupled to said first input/output ports, said multiplexer  
5 interface being adapted to receive said data packets;  
6 a multiplexer coupled to said multiplexer interface, said multiplexer being  
7 adapted to receive said data packets from said multiplexer interface and to multiplex  
8 said data packets;  
9 a transmitter coupled to said multiplexer; and  
10 an optical link coupled to said transmitter, said transmitter being adapted to  
11 transmit the multiplexed data packets over said optical link to a receiver;  
12 wherein said multiplexer interface comprises a first optical transceiver adapted to  
13 detect a first loss of signal in at least one of said first Gigabit Ethernet links; to generate  
14 a signal loss code insert in response to detection of said first loss of signal; and to apply  
15 said signal loss code insert to said multiplexer using a Gigabit Ethernet protocol in  
16 place of said data packets from said at least one of said first Gigabit Ethernet links  
17 having said first loss of signal.

1 2. (Previously presented) The system of claim 1, further comprising:  
2 said receiver, which is coupled to said optical link and is adapted to receive said  
3 multiplexed data packets from said optical link;  
4 a demultiplexer coupled to said receiver, said demultiplexer being adapted to  
5 demultiplex the received multiplexed data packets; and  
6 a demultiplexer interface coupled to said demultiplexer, said demultiplexer  
7 interface being adapted to receive the demultiplexed data packets,  
8 wherein said demultiplexer interface comprises a plurality of second optical  
9 transceivers that are each adapted to be coupled to a plurality of second Gigabit  
10 Ethernet links;

Serial No. 09/502,882

11 and wherein said demultiplexer interface is adapted to prevent at least one of  
12 said second optical transceivers from transmitting light in response to receipt of said  
13 signal loss code insert within the demultiplexed data packets.

1 3. (Original) The system of claim 2, further comprising a photo-  
2 detector circuit coupled to said demultiplexer;  
3 wherein said photo-detector circuit is adapted to detect a  
4 second loss of signal in said optical link and in response,  
5 generate a deactivate signal and transmit the deactivate signal  
6 to said second optical transceivers.

1 4. (Previously presented) The system of claim 2, wherein each of said second optical  
2 transceivers comprises a physical layer chip,  
3 adapted to detect a third loss of signal in one of said second  
4 Gigabit Ethernet links and go into an auto-negotiation stage.

1 5. (Original) The system of claim 1, wherein said signal loss code  
2 insert is bit multiplexed with said data packets.

1 6. (Currently amended) The system of claim 1, wherein said multiplexer is  
2 ~~adapted to multiplex~~ multiplexes on a bit by bit basis.

1 7. (Currently amended) A method of communicating the existence of  
2 faults in a data transmission system, said method comprising:  
3 receiving a plurality of data packets carried on a plurality of first Gigabit Ethernet  
4 links at a first plurality of Gigabit Ethernet input/output ports;  
5 multiplexing said data packets;  
6 transmitting the multiplexed data packets to a receiver along at least a portion of  
7 an optical link;  
8 detecting a first loss of signal in at least one of said first Gigabit Ethernet links  
9 and generating a signal loss code insert in response to detecting said first loss of signal;  
10 and

Serial No. 09/502,882

11 transmitting said signal loss code insert using a Gigabit Ethernet protocol to said  
12 receiver in place of said data packets from said at least one of said first Gigabit Ethernet  
13 links having said first loss of signal.

1 8. (Previously presented) The method of claim 7, said optical link coupled to a  
2 demultiplexer, said demultiplexer comprising a plurality of second optical transceivers  
3 that are each adapted to be coupled to a plurality of second Gigabit Ethernet links, said  
4 method further comprising:  
5 receiving said signal loss code insert; and  
6 preventing at least one of said second optical transceivers from transmitting light in  
7 response to said signal loss code insert.

1 9. (Original) The method of claim 7, wherein a photo-detector circuit  
2 is coupled to said demultiplexer, said method further comprising:  
3 detecting a second loss of signal in said optical link;  
4 generating a deactivate signal in response to said second loss of signal; and  
5 transmitting the deactivate signal to said second optical transceivers.

1 10. (Previously presented) The method of claim 7, wherein each of said second optical  
2 transceivers comprises a physical layer chip,  
3 said method further comprising said physical layer chip  
4 detecting a third loss of signal in one of said second  
5 Gigabit Ethernet links; and  
6 entering into an auto-negotiation stage.

1 11. (Previously presented) The method of claim 7, wherein said transmitting said signal  
2 loss code insert to said receiver in place of said data packets comprises bit multiplexing  
3 said signal loss code insert with said data packets.

1 12. (Previously presented) The method of claim 7, wherein the multiplexing is  
2 accomplished on a bit by bit basis.

1 13. (Cancelled)

Serial No. 09/502,882

1 14. (Cancelled)

1 15. (Currently amended) A multiplexer interface comprising:

2 a plurality of input ports, each input port being adapted to receive data from a  
3 respective input link,

4 a plurality of output ports, the data received by each input port being applied to a  
5 corresponding one of said output ports,

6 means for detecting a loss of signal at any one of said input ports,

7 means for generating a fault-identifying signal in response to detecting said loss  
8 of signal, and

9 means for applying said fault-identifying signal using a Gigabit Ethernet protocol  
10 to the output port corresponding to one of said input ports having said loss of signal in  
11 place of said data.

1 16. (Previously presented) The multiplexer interface of claim 15, wherein said data are  
2 carried in packets of variable length and wherein said data are encoded using a  
3 predetermined code.

1 17. (Previously presented) The multiplexer interface of claim 16, wherein said fault  
2 identifying signal is a signal that said predetermined code does not produce.

1 18. (Currently amended) A multiplexer interface, comprising:

2 at least one input port, said input port being adapted to receive data from a  
3 respective input link,

4 at least one output port, the data received by said input port being applied to said  
5 output port,

6 means for detecting a loss of signal at said input port,

7 means for generating a fault-identifying signal in response to detecting said loss  
8 of signal, and

9 means for applying said fault-identifying signal using a Gigabit Ethernet protocol  
10 to said output port having said loss of signal in place of said data.

Serial No. 09/502,882

1 19. (Previously presented) The multiplexer interface of claim 18, wherein said data are  
2 carried in packets of variable length and wherein said data are encoded using a  
3 predetermined code.

1 20. (Previously presented) The multiplexer interface of claim 19, wherein said fault  
2 identifying signal is a signal that said predetermined code does not produce.

1 21. (Previously presented) The system of claim 1, wherein said signal loss code insert  
2 is transmitted continuously by said transmitter as long as said first loss of signal is  
3 detected.

1 22. (Previously presented) The method of claim 7, wherein said signal loss code insert  
2 is transmitted continuously as long as said first loss of signal is detected.

1 23. (Cancelled)

1 24. (Cancelled).

1 25. (Previously presented) The multiplexer interface of claim 15, wherein said fault-  
2 identifying signal is applied to said output port continuously as long as said loss of  
3 signal is detected.

1 26. (Previously presented) The multiplexer interface of claim 18, wherein said fault-  
2 identifying signal is applied to said output port continuously as long as said loss of  
3 signal is detected.